

K-DIGIT PRAEZ DRUCKSCHA ISE

Digital pressure switch ISE

Свойства	
Конструкция	Precision Digital Pressure Switch for excess pressure
Изпълнение	with switching function display unit
макс. изходящо налягане	1,05 MPa
мин. изходящо налягане	-105,00 kPa
макс. номинално налягане	1,0 MPa
мин. номинално налягане	-100,0 kPa
време за задействане	max. 2,5 ms
номинално напрежение	12 to 24 VDC
Контролно налягане	1,50 MPa
вид защита	IP 65
разход на електроенергия	80 mA
Разрешително	CE, UL/CSA, RoHS
температура на средата	-5 °C to +50 °C
околна температура	-5 °C bis +50 °C
Течности	Compressed air, non-corrosive gases, non-flammable gases
серия	ISE40A
Други данни	Compact, design user-friendly operation Copy function to copy settings on up to 10 sub-sensors Energy saving function automatically switches off the display after 30 seconds Anti-chattering function, selectable units, Adjustable hysteresis Extended connection cable to 3.00 m Pre-wired M12 connector with 4 pins (Lead wire length 100 mm)



Описание

Digital precision pressure switch for overpressure, series ISE40A, 3 1/2-digit, 7-segment display, 2-colour (red/green), compact design, user-friendly operation, copy function, settings can be copied to up to 10 subordinate sensors, energy saving function, the display switches off automatically after 30 seconds, anti-chattering function, free choice of units, adjustable hysteresis, 2 m connection cable with plug included

Артикул

Обозначение	точност при възпроизвеждане	съединение пневматично	електрически изход
K- 07 50 00 06	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 07	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 08	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 09	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 10	±2 %	R 1/8 (M 5-internal thread)	NPN open collector, 2 Outputs + Copyfunction
K- 07 50 00 11	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 12	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 13	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 14	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 15	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 16	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 17	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 18	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 19	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 20	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 21	±2 %	M 5 x 0,8 (internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 22	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 23	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 24	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 25	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 26	±2 %	G 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 27	±2 %	G 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input