K-DIGIT PRAEZ DRUCKSCHA ISE

Digital pressure switch ISE

Vlastnosti

Konstrukce	Precision Digital Pressure Switch for excess pressure
Provedení	with switching function display unit
Max. tlak na výstupu	1,05 MPa
Min. tlak na výstupu	-105,00 kPa
Max. jmenovitý tlak	1,0 MPa
Min. jmenovitý tlak	-100,0 kPa
Doba odezvy	max. 2,5 ms
Jmenovité napětí	12 to 24 VDC
Zkušební tlak	1,50 MPa
Stupeň krytí	IP 65
Odběr proudu	80 mA
Osvědčení	CE, UL/CSA, RoHS
Teplota média	-5 °C to +50 °C
Teplota okolí	-5 °C bis +50 °C
Média	Compressed air, non-corrosive gases, non-flammable gases
Řada	ISE40A
Další údaje	Compact, design user-friendly operation Copy function to copy settings on up to 10 sub-sensors Energy saving function automatically switches off the display after 30 seconds Anti-chattering function, selectable units, Adjustable hysteresis Extended connection cable to 3.00 m Pre-wired M12 connector with 4 pins (Lead wire length 100 mm)



Popis

Digital precision pressure switch for overpressure, series ISE40A, 3 1/2-digit, 7-segment display, 2-colour (red/green), compact design, user-friendly operation, copy function, settings can be copied to up to 10 subordinate sensors, energy saving function,
the display switches off automatically after 30 seconds, anti-chattering function, free choice of units, adjustable hysteresis, 2 m connection cable with plug included

Výrobek

Označení	Přesnost opakování	Přípoj pneumatický systém	Elektrický výstup
K- 07 50 00 06	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 07	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 08	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 09	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 10	±2 %	R 1/8 (M 5-internal thread)	NPN open collector, 2 Outputs + Copyfunction
K- 07 50 00 11	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 12	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 13	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 14	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 15	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 16	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 17	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 18	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 19	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 20	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 21	±2 %	M 5 x 0,8 (internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 22	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 23	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 24	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 25	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 26	±2 %	G 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 27	±2 %	G 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input

Navzdory nejpečlivější kontrole nemůžeme vyloučit chyby a nepřejímáme žádnou záruku za obsažené údaje.