

HK SP CAER

Coil for solenoid-operated directional control valve HK DKER



Properties

| | |
|--------------------------|------------------------------------|
| Scope of supply | with O-ring |
| Corresponding connectors | HKSP664, HKSP666, HKSP667, HKSP668 |



Note

As far as AC coils are concerned, power input is considerably higher in the take-up phase than in the stopping phase. These must therefore never be operated without a magnet core since there is a danger of overheating and the coil can burn through. A similar effect occurs if valves with AC magnets are operated with extremely high pulse frequencies (On / Off). In such cases the coils, which are often in the vicinity of the high power input, can also overheat. For such applications the use of RC coils with rectifier plugs is recommended. With DC coils extremely high power spikes can occur during powering down. We therefore recommend the use of plugs with protective circuits when using such coils.

Tightening torque for attaching nuts of the solenoid coils: 3Nm

Ordering information

Other types of coil on request

Item

| Identification | Rated voltage/ current type | for valve type | Average power consumption (W) | Weight (kg) |
|------------------|--------------------------------|----------------|----------------------------------|----------------|
| HK SP CAER 110AC | 110/50/60 VAC | HK DKER | 95 | 0,52 |
| HK SP CAER 230AC | 230/50/60 VAC | HK DKER | 95 | 0,52 |

Accessories

| | |
|-----------------|--|
| HK SP DIN 43650 | Electrical plug for solenoid coil DIN 43650 / ISO 4400 |
|-----------------|--|