K-DIGIT PRAEZ DRUCKSCHA ISE

Digital pressure switch ISE

Īpašības

Modelis	Precision Digital Pressure Switch for excess pressure
Modelis	with switching function display unit
maks. izejas spiediens	1,05 MPa
min. izejas spiediens	-105,00 kPa
maks. nominālais spiediens	1,0 MPa
min. nominālais spiediens	-100,0 kPa
Aktivizēšanas laiks	max. 2,5 ms
Nominālais spriegums	12 to 24 VDC
Izmēģinājuma spiediens	1,50 MPa
Aizsardzības veids	IP 65
Strāvas patēriņš	80 mA
Apstiprinājums	CE, UL/CSA, RoHS
Vielas temperatūra	-5 °C to +50 °C
Vides temperatūra	-5 °C bis +50 °C
Darba vides	Compressed air, non-corrosive gases, non-flammable gases
Sērija	ISE40A
Papildu dati	Compact, design user-friendly operation Copy function to copy settings on up to 10 sub-sensors Energy saving function automatically switches off the display after 30 seconds Anti-chattering function, selectable units, Adjustable hysteresis Extended connection cable to 3.00 m Pre-wired M12 connector with 4 pins (Lead wire length 100 mm)



Apraksts

Digital precision pressure switch for overpressure, series ISE40A, 3 1/2-digit, 7-segment display, 2-colour (red/green), compact design, user-friendly operation, copy function, settings can be copied to up to 10 subordinate sensors, energy saving function,
the display switches off automatically after 30 seconds, anti-chattering function, free choice of units, adjustable hysteresis, 2 m connection cable with plug included

Izstrādājums

Apzīmējums	Atkārtošanas precizitāte	Pneimatiskais pieslēgums	Elektriskā izeja
K- 07 50 00 06	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 07	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 08	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 09	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 10	±2 %	R 1/8 (M 5-internal thread)	NPN open collector, 2 Outputs + Copyfunction
K- 07 50 00 11	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 12	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 13	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 14	±2 %	R 1/8 (M 5-internal thread)	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 15	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 16	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 17	±2 %	for hose outer-Ø 4 mm	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 18	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 19	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 20	±2 %	for hose outer-Ø 6 mm	PNP open collector, 2 Outputs + Copyfunction
K- 07 50 00 21	±2 %	M 5 x 0,8 (internal thread)	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 22	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 23	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 24	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 25	±2 %	Rc 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input
K- 07 50 00 26	±2 %	G 1/8	PNP open collector, 2 Outputs + analog Voltage/Auto-Reference Input
K- 07 50 00 27	±2 %	G 1/8	PNP open collector, 2 Outputs + analog Ampere/Auto-Reference Input

Neskatoties uz rūpīgu pārbaudi, mēs nevaram izslēgt kļūdas un negarantējam iekļautās informācijas pareizību.